

## Equipamiento para Montaje

Vibrador	Kit de Montaje
Series MICRO™	XHD-MB12
XHD-A1T XHD-C1T	
CDS36-210 CD36-210	XHD-MB18
CDS18-70 CD18-70	
XHD-A1.5T XHD-C1.5T	
XHA-A0.5T XHA -C0.5T	
CDS36-390 CD36-390	XHD-MB18-2
CDS18-170 CD18-170	
XHD-A2T XHD-C2.5T	
XHA-A1.5T XHA-C1.5T	
CDS36-650 CD36-650	XHD-MB30
CDS18-470 CD18-470	
XHD-A5T XHD-C5T	
XHA-A3.5T XHA-C3.5T	
CDS36-1040 CD36-1040	XHD-MB30-8
CDS18-910 CD18-910	
CDS18-1300 CD18-1300	
XHD-A8T XHD-C8T	
XHA-A6.5T XHA-C6.5T	
XHA-A8.5T XHA-C8.5T	
CDS36-1660 CD36-1660	XHD-MB36
CD18-1670 CD18-2150	
XHD-A12T XHD-C12T	
XHA-C11.5T	
CD36-2900	XHD-MB36-16
XHD-C16T	

## Equipamiento para Montaje

VIBRATOR MOUNT BRACKET DIMENSIONS							
MB-12	A	B	C	D	E	F	G
XHA-0.5,1.5	12(305)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.25(6)
XHD-1.5	12(305)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.25(6)
PKL 135,150	12(305)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
MB-18							
XHA-0.5,1.5,2T	18(457)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
XHD-1.5,2.5T	18(457)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
NTS 350,75/01,50/01	18(457)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
PKL 170,200,220	18(457)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
NCT-5,10,10I	18(457)	5.5(140)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
MB-24							
NCT-15,29,29I	24(610)	6(152)	6(152)	5(127)	0.25(6)	1.5(38)	0.38(10)
MB-30							
XHA-3.5,6.5,8.5T	30(762)	7.25(184)	7.5(191)	6.5(165)	0.38(10)	1.5(38)	0.38(10)
XHD-5,6.5,8T	30(762)	7.25(184)	7.5(191)	6.5(165)	0.38(10)	1.5(38)	0.38(10)
NTS 54/02,50/04	30(762)	7(178)	7.5(191)	6.5(165)	0.25(6)	1.5(38)	0.38(10)
NCT-55,108,108I	30(762)	7(178)	7.5(191)	6.5(165)	0.25(6)	1.5(38)	0.38(10)
MB-36							
XHA-11.5T	36(914)	8.75(222)	11(279)	8(203)	0.38(10)	1.5(38)	0.5(13)
XHD-12,16T	36(914)	8.75(222)	11(279)	8(203)	0.38(10)	1.5(38)	0.5(13)
NCT-126,250,250I	36(914)	8.75(222)	11(279)	8(203)	0.38(10)	1.5(38)	0.5(13)
inches(mm)							

### STANDARD "H" TYPE VIBRATOR MOUNT BRACKET

